

# Axessor QSM

## Electronic Time Lock

### Product Specifications

#### Time Lock Functions

- Weekly Time Lock
- Holiday Periods
- Time delay
- Duress Time Delay

**Note:** Even valid user code cannot be used to open the lock during weekly time lock and holiday periods



#### Codes

- 1 Master Code
- 2 Manager Codes
- 18 User Codes (in 2 groups of 9 each)
- 1 Courier Code

#### Code Functions

- Single Mode (1 x 6 digits)
- Dual Mode (2 x 6 digits)
- Duress Code (silent alarm)
- Shelve Function
- Penalty after 4 wrong codes (5 mins)

#### Audit

- 5000 events with date and time stamps.  
Protected against manipulation and power failure.
- Non-erasable opening counter

#### I/O Connection

- 1 Input: Door contact.
- 1 Output: Potential free contact for alarms (30VDC / 2A, 50 VAC / 0.5A with resistant load). Duress Alarm, Bolt Position, Additional trigger contact programmable.  
Selectable polarity (NO or NC) for both input and output.

#### Input Unit

- Robust metal housing
- Silicon keypad with yellow navigation keys
- Large, Multilingual LC display (9 Languages)
- Built-in USB interface
- Integrated battery compartment
- Buzzer

#### Lock Unit

- Motorised lock with automatic locking
- 5 N moving force in both directions
- Programmable bolt open time (6-99 seconds)

#### Power Supply

- 3 x 1.5 volt Alkaline batteries LR6/AA  
Battery level warning at 20%

#### Programming

- Programming software with USB Security Dongle or over keypad of input unit (not all functions)

#### Approvals/ Certificates

